



ETA716 16 位数字 IO 扩展模块使用手册

ETA716 16**IO**

ETA716

5

B 402#

610041

028-86180660

028-85141028

<http://www.emtronix.com>support@emtronix.com.cn

1

ETA716 16 IO
 ETA716 ISA 8 8
 300H outportb (0x300, value)
 value = inportb (0x300) 1.3 inch× 1.6 inch 1
 inch = 2.54cm

2

CN1 ISA 20 IDC
 CN1

	CN1		
	PIN#	PIN#	
RESET#	1	2	SA0
SD0 LSB	3	4	SA1
SD1	5	6	SA2
SD2	7	8	SA3
SD3	9	10	SA4
SD4	11	12	WE#
SD5	13	14	RD#
SD6	15	16	CS1# I/O
SD7 MSB	17	18	VCC
IRQ	19	20	GND

CN2 IO 20 IDC OUTPUT0 INPUT0
 300H D0 OUTPUT7 INPUT7 300H D7

	CN2		
	PIN#	PIN#	
OUTPUT0	1	2	INPUT0
OUTPUT1	3	4	INPUT1
OUTPUT2	5	6	INPUT2

OUTPUT3	7	8	INPUT3
OUTPUT4	9	10	INPUT4
OUTPUT5	11	12	INPUT5
OUTPUT6	13	14	INPUT6
OUTPUT7	15	16	INPUT7
VCC +5V	17	18	VCC +5V
GND	19	20	GND